

Operation

The INDI 16X-Pro will operate from a 12 volt automobile battery or any 110-120V AC outlet with a minimum of 4 amps capacity. It will operate with less amperage, but the charge current will be limited to the maximum capacity of the supply. If the power source is not rated for at least 50% of the charge current set on the INDI 16X-Pro, the charge may terminate early.

CAUTION: If you use an automotive battery as the power source, make sure you have good ventilation. Lead-acid batteries release explosive hydrogen gas when they are being charged.

If an overload occurs or improper connection is made, the fuse will blow. In this case, disconnect the power and send the unit to a service center for repair. We charge a flat fee of \$20.00 to reset the unit. NEVER attempt to repair or open the charging unit, the unit contains no user replaceable part.

The long 3 foot lead must connect to an 110V AC outlet first. Then connect the 3 foot lead to the back of the charger, the unit will beep and the mode LED will be on. This indicates the charger is operational. The leads supplied for the battery pack hook-up are the alligator type. Be sure to observe polarity when connecting to your battery pack (Positive to red and negative to black). Damage may result if polarity is reversed. Do not change connectors or wires on the unit. Changing connector(s) or wires on the unit can affect performance drastically and void the mfg. warranty.

The INDI 16X-Pro is equipped with four optimized charge & discharge profiles. There are 4 different selectable operational modes of operation on the INDI 16X-Pro. You can select the different modes by pressing the start button differently. Each time the start button is pressed, the charger waits 2 seconds to see which mode you would like to select. You may select the 4 different charge modes as follow:

Mode 1, Fuzzy Logic Charge *Press Once and Release:*

This mode will discharge the battery pack at 4 amp until the pack reaches 2.5 volts. Then it will trickle charge the pack for 10 seconds before going into fast charge. During charging, the INDI 16X-Pro constantly collects data, input voltage, output voltage and current, and stores them in its memory. Then, the unit generates high resolution moving averaged data sets. The fuzzy logic program then monitors the stored data sets and compares them to its built-in memory bank. When a matched pattern is detected, the unit stops fast charging and beeps every 30 seconds to remind the user that fast charging is completed. The unit trickle charges the battery pack after fast charging.

Mode 2, Delta Peak Charge *Press Once and Hold:*

This mode will do a standard peak detection charge. It will peak the battery pack and then goes into trickle charge.

Mode 3, Discharge At 4 Amp *Press Twice and Release:*

This mode will discharge the battery pack at 4 amp and automatically cut-off when the pack reaches 2.5 volts. The 4 amp discharge rate is good for conditioning battery packs. It will maintain the performance of new packs and revive the performance of old packs. Higher discharge rates can be applied and (20A to 30A) are recommended only on individual cells, however, the life and performance of the battery may reduce drastically. Battery matchers apply 20 amps to 30 amps discharge rates because they need to attain simulated run-time of individual cells for the purpose of matching battery packs.

Mode 4, Condition *Press Twice and Hold:*

This mode will perform a mode 1 operation and a mode 3 operation sequentially. There is a 30 seconds delay in between.

Safety Precautions

1. Do not leave the battery and charger unattended while in use.
2. Do not operate the charger near water.
3. Do not replace the internal fuse. Send the unit back for repair.
4. Never connect the charger to an automobile while its engine is running.
5. This charger is not intended for use by unsupervised children.
6. This charger is designed for R/C car high power rechargeable battery only.
7. When charging, constantly monitor the temperature of the battery pack. If your battery pack becomes hot, discontinue the charging operation immediately.
8. Carefully observe connector polarities at all times.

Warranty and Repair

Your INDI charger is guaranteed against workmanship and manufacturing defects for a period of 30 days from the original date of purchase. This warranty is limited to the original purchaser of the charger and is not transferable. Warranty repair will not cover units which have been modified, missed or serviced by an unauthorized service center.

NOTE: Freight charges are not covered by warranty. Repair fee within 30 to 90 days of purchase: \$20.00 Repair fee within 90 to 180 days of purchase: \$35.00

If your INDI charger needs repair:
1. Ship the charger in its original box, freight prepaid to:

INTEGY INC.
1140 Centre Dr #E
City of Industry CA 91789

Distributed by Integy Inc.

or you may call us at (909)444-2766 for our current street address.

Include your complete name and address information inside the box, and write address on the outer label/return address area.

2. Include a brief summary of the difficulty. Date your correspondence and be sure your name and address appear on this enclosure. Also, include a phone number where you can be reached during the day time.

To receive warranty service you must include your original dated sales receipt to verify your proof-of-purchase date. Providing that warranty conditions have been met, your charger will be repaired free of charge. We charge a flat fee of \$20.00 for handling, shipping & diagnostic if we can not detect any problem with the unit and the unit will only be returned via UPS GROUND C.O.D.. Should your repair cost exceed 50% of the retail purchase cost, you will be provided with an estimate advising you of your options. Any return freight for non-warranty repairs will be charged to the customer. For non-warranty repairs, please advise us of the payment method you prefer to use. Specify Visa or MasterCard, or we can return C.O.D. cash only. (C.O.D. charges are \$5.00 extra.) If you prefer to use a credit card, include your card number and expiration date.

In no case shall our liability exceed the product's original cost. We reserve the right to modify the provisions of this warranty without notice.

Because Integy Inc. has no control over the use of the charger, no liability may be assumed nor will liability be accepted for any damage resulting from using this product. Every INDI charger is thoroughly tested and cycled before leaving our distribution facility and is, therefore, considered operational. By the act of operating this charger, the user accepts all resulting liability.